

## Digital Thermometer WT-2

Temperature range: -50 +300 C(-58-+572 F )

Resolution: 0.1 C

Accuracy: (-20-80C)± 1

Voltage: DC1.5V

Machine Dimension: 107 × 66 × 24mm

Probe rod length: 198 mm

Display Size: 33.5 × 14.5mm

Function:

Switch display

Retention of data

Maximum and minimum temperature memory function

Maximum and minimum temperature setting and alarm function

Key Features:

ON/OFF Used to switch the machine

HOLD To retain data

SET Set alarm

ADJ Set up recycling

AC Cancel alarm

OK Enter/Confirm

MAX/MIN Maximum and minimum temperature

Switch display

Instructions:

ON/OFF Click button to open the thermometer into the measurement mode SET Click here to enter alarm setting mode ADJ/OK ) of the model, "HI" and high-temperature warning lights flashing that high-temperature alarm settings.

Two seconds press and hold the ADJ can be increased by 1 until they reach high temperature alarm limits, when the temperature is higher than 300 higher than when they return to the low temperature alarm limits on the state of 1, when the adjustment of temperature to high temperature by the temperature alarm OK button to confirm. "Lo" said low-temperature alarm light blinking into the low temperature alarm settings.

In accordance with these steps to install the required low-temperature alarm and then press the OK button to confirm.

After the completion of set up, "Hi" or "Lo" will disappear, "AL" indicates that the alarm mode to enter