



VICTOR 6052&VICTOR 6050 - Features and Benefits

- Clamp open:55mm
- Diode test, Continuity Buzzer,Low battery indication
- Auto power off, Data hold/Peak hold,Manual range
- Relative value measurement

Specifications

Specification	Basic Function	Range	Basic accuracy	
			VICTOR 6052	VICTOR 6050
DC Voltage		400mV/4V/40V/400V	----	±(0.5%+4d)
		4V/40V/400V	±(0.5%+4d)	----
		1000V	±(1.0%+6d)	±(1.0%+6d)
DC Current		400A	±(2.5%+20d)	±(2.5%+20d)
		2000A	±(3.5%+20d)	±(3.5%+20d)
AC Voltage		400mV	±(1.6%+8d)	±(1.6%+8d)
		4V/40V/400V	±(0.8%+10d)	±(0.8%+10d)
		750V	±(1.0%+10d)	±(1.0%+10d)
AC Current		400A	±(2.5%+20d)	±(2.5%+20d)
		2000A	±(3%+10d)	±(3%+10d)
Resistance		400Ω	±(0.8%+5d)	±(0.8%+5d)
		4kΩ/40kΩ/400kΩ/4MΩ	±(0.8%+4d)	±(0.8%+4d)
		40MΩ	±(1.2%+10d)	±(1.2%+10d)
Capacitance		40nF	±(5.0%+30d)	±(5.0%+30d)
		400nF/4μF/40μF	±(3.5%+8d)	±(3.5%+8d)
		100μF	±(5.0%+10d)	±(5.0%+10d)
Frequency		5.120Hz/51.20Hz/512.0Hz/5.120kHz/51.20kHz/512.0kHz/100.0kHz	±(0.5%+4d)	±(0.5%+4d)